



STRATCO

GARAGE DOOR OPENER RDO12

FOR ROLLER GARAGE DOORS | INSTALLATION & USER GUIDE

INSTALL GUIDE



CAUTION: Activate operator only when the door is in full view, free of obstructions and properly adjusted. Do not enter or leave the garage while the door is in motion. Do not allow children to play near the door.

Disconnect electric power to the garage door operator before making repairs or removing covers.

IMPORTANT: Fix the caution label to the rear of the garage door as a reminder of safe operating procedures.

PREINSTALLATION NOTE




figure 1

right hand installation shown(inside looking out)


N.B.: The right hand and left hand installation could be swaped if you wish
Please refer to control box set up.

Check that there is sufficient side clearance to fit the operator unit. It may be fitted to either the right or left hand side.

(1) Minimum side clearance:

The minimum side clearance between door curtain and the inside edge of mounting bracket is 85mm;


The minimum side clearance between door curtain and the outside edge of mounting bracket is 135mm.



(2) Recommended side clearance

The recommended side clearance between door curtain and the inside edge of mounting bracket is 110mm;

The recommended side clearance between door curtain and the outside edge of mounting bracket is 160mm.



If the operator is being fitted at the same time as the new door installation, read these instructions in conjunction with the STRATCO roller door installation instructions.

If the operator is being retro-fitted, make sure the door operates smoothly and is properly balanced.

N.B.: SPECIAL CARE SHOULD BE TAKEN IF RE-TENSIONING OF THE DOOR IS REQUIRED.

At no stage should you loosen both "U" bolts if door is under tension.

IF THERE ARE ANY PROBLEMS PLEASE CONTACT YOUR LOCAL SUPPLIER OF THIS OPERATOR




INSTALLATION INSTRUCTIONS

STEP 1

Whilst the door roll is on the floor, rotate shaft backwards and forwards by hand and then release. This action will allow the roll to centralize itself on the shaft. (New installation only).

STEP 2

Slide drive unit onto shaft as shown Figure 5. ensuring drive lugs engage fully with the narrowest spoke on drum wheel.



N.B.: Right-hand installation shown (inside looking out)

Lift door onto mounting brackets (ensuring curtain roll is round in correct way) centralize curtain roll with opening. Refer to door installation instructions. (New installations only).

Ensure motor assembly is fully engaged with drum wheel spokes. Clamp shaft to mounting brackets using "U" Bolts supplied. (Use "U" bolt in opener pack for MOTOR end). See Figure 6.

Disengage the motor drive by pulling the manual release string downwards. See Figure6.

Tension door and complete door installation as per Door Installation Instructions. Ensure door is correctly balanced and is not binding or sticking within vertical tracks.

Ensure locking bars (if fitted) are moved to the retracted (unlocked) position and keys removed from the lock.

Mount Control Unit approximately 1.6m from the floor out of the reach of children. Use No.4X1" self-tapping screws and rawplugs supplied. Ensure aerial is clear of all steel supports and coiled electrical leads. Fit plug from motor unit into bottom of Control Box.

Connect the control unit power cord to an adjacent socket. Ensure that the socket is properly earthed.

SETTING TOP AND BOTTOM LIMITS FOR RIGHT HAND INSTALLATION

N.B.: Switch1(2) in "on" position is for right hand installation;
Switch1(2) in "off" position is for left hand installation.

STEP 1


Remove Limit Switch Cover Plate (See Figure 6) by carefully prising off with a small screwdriver.

STEP 2

Top limit cam "T" controls open position of door. Bottom limit cam "B" controls closed position of door.

STEP 3

Slightly loosen the three retaining screws so that the cams can be easily moved (See Figure 7).



STEP 4

Ensure that the manual release lever is still in the "disengaged" position, and manually raise the door until it is approx 100mm from the top stop position.

STEP 5

Rotate cam "T" (in the same direction that is moving as you were manually raising the door) so that it actuates the top Limit Switch.

STEP 6

Manually lower the door until it is touching the ground .

STEP 7

Rotate cam "B" (in the same direction that is was moving as you were manually lowering the door) so that it actuates the bottom Limit Switch.

STEP 8

Tighten the three retaining screws so that the cams will not move.

STEP 9

Manually position door to halfway and re-engage the motor drive by moving the manual release lever to the "engage" position. N.B.: Door can now only be operated electrically, not manually. If you wish to return to manual operation, ensure power is switched off and move lever to "disengage" position.

IMPORTANT: When the door is traveling in the 'Up' position, hold bottom rail. The door should overload and stop. If it does not, reverse motor wires (Spade Connections.)

You will need to re-adjust the Limit Cams as they will be working in a different direction.

STEP 10

Press Button on Control Box Front and check closing and stopping position.

STEP 11

If you are achieving the desired stop position, then replace the Limit Switch Cover Plate. If not, then reset the Limit Cams (Steps 2-to 9_) after first turning off the mains power.

STEP 12

Once the limits have been set, fit the additional security screws(2 off self-tapping screws supplied) with the door in manual mode. With the door fully closed, mark the panel at the first point where the curtain roll touches the drum wheel, on both ends of the curtain (See Figure 9).

Raise the door slightly so that the marks can be seen and accessed from inside the garage.

Fit the security screws through the bottom of a corrugation and into the plastic flange of the drum wheel, on both ends of the curtain. Tighten securely.

WARNING! –Do not run door on power through its full travel until the limits are correctly set.

STEP 13

Auto close option

switch1(1) in "on" position: auto close features on;
switch1(1) in "off" position: auto close features off.

N.B: mandatory Photo Eye Protection must be used for this option.
Contact your local supplier.

Figure 8






Figure 9



i) Door fully closed ii) Door slightly closed

CONTROL BOX SET UP

Remove cover on front of control box



1. Wiring diagram

- B1, B2(AC24V): transformer output
 M1, M2 : motor
 X4(-/+24) : infrared beam, X4I: signal input
 LAMP : 36V 1.5W light socket
 X3 : remote control receiver

Key 1

Key 3



Key 2

Key 4

3. Sensitivity adjustment

For right hand installation:

- 1)adjust pot RF2 for downward traveling sensitivity, clockwise is for big force and the anti-clockwise is for small force.
- 2)adjust pot RF2 for upward traveling sensitivity, clockwise is for big force and the anti-clockwise is for small force.

Whilst the door is travelling turn the obstruction sensitivity pot slowly until an overload condition occurs i.e. door going up stops before reaching the set top limit or door going down auto-reverses before reaching set bottom limit. Cycle the door a few times ensuring an overloading conditions is not registered during normal operation.

PROGRAMMING HANDSETS TO NEW CONTROL BOX

Press and release the black learning button "S1" learn LED indicator will light and go out, then press the handset key which will operate the door, the handset transmitter is now programmed.

* For multiple handsets code them the same as above mentioned.

To delete all codes

Press and hold the learning button "S1" in the control box for 15 seconds until the LED indicator go out, all transmitters codes held in the memory have been erased.

N.B.: If a transmitter is lost or stolen please erase the memory and re-learn any spare or new transmitters.

OWNER'S MANUAL

DOOR OPERATION

A roller door equipped with a roller door operator may be operated by any of the following two methods:
by using the hand held Transmitter;

by depressing the push button on the control box.(mounted on the wall)

! WARNING

- Ensure that the Centre Lift Lock is not engaged when the Drive Unit is in the automatic position.

Manual Operation

In the case of a power failure, the drive unit has an easily accessible manual release string, the door could be opened manually by using the release string.

Obstruction Detection

During an open cycle if an obstruction is detected the door will stop.

During a closing cycle if an obstruction is detected the door will reverse to the open position. The sensitivity or the amount force required to cause an obstruction detection is fully adjustable.

Courtesy Light

An internal courtesy light is housed within the control box enclosure. This is activated during an open or close cycle and will stay illuminated for approximately 3 mins

Automatic Closing

The operator can be programmed to automatically close from 5 to 60 seconds after the door has been opened.

Photo-electric sensor

The operator includes an interface for the connection of a photo-beam sensor.

The Photo-beam sensor can be supplied if accessory

OPERATING CONTROLS

1)Control Box Push Button

Pressing this button will open, close or stop the door.

2)Hand transmitter

Each button is programmed to have three functions to open, close and stop the door.

Technical Specifications

INPUT VOLTAGE: 220VAC+/-10% 50Hz
(110VAC 60Hz or 127VAC 60Hz available on request)
Single Phase

TRANSFORMER SEPC: Primary Voltage 220VAC
Secondary Voltage 24VAC

WORKING CIRCUMSTANCE: TEMPERATURE: -20°C~70°C

MOTOR SPEC: Motor Type Permanent Magnet D.C. Motor
Voltage 24V DC

CONTROL BOARD SPEC: Control Board Voltage 24V DC / 5V DC
Light Glove Voltage 36V 1.5W
Receiver specification Receiver type FSK AM
(built-in) RF Frequency 303 MHz
Control distance 50m max.

TRANSMITTER SPEC: Carrier Frequency 303 MHz
Current Consumption 50mA(approx)
Battery Voltage 12 Volts A27 battery
Coding Format Rolling Code

ACCESSORY OPTIONS

Additional remote control transmitter
Infrared beam Additional safety feature
Manual release lock
External receiver

ACCESSORY OPTIONS

Additional remote control transmitter



Infrared beam additional safety feature



External receiver

