

FAAC Receiver Types Photos.

To program a remote in it is the same way exactly as the China ones we use.



FAAC
White Owl
CHANNEL
Small Bolton



FAAC White: 2 CHANNEL SMALL Button



After the transmitter has been learnt, the receiver remains in learning mode for 10 seconds (The LED stays on continuously). This is to allow more transmitters to be taught if required, (up to 256 transmitters). 10 seconds after the final transmitter has been taught, the receiver automatically exits from learn mode and the LED goes off. Alternatively to bring the receiver out of learn mode, press either button on the receiver.

Adding Extra Transmitters:

New transmitters can be added in the same way as above. It is also possible to put the receiver into learning mode without having access to the receiver button. This is done using a learnt transmitter. To do this, press transmitter buttons F1 and F2 simultaneously (for at least 5 seconds) and then pressing a